

UNC Charlotte, ECGR 6185/8185, Spring 2013: Lab 3

Analog sensor & the TI MSP430

Learning Objectives

This lab will have students read an analog accelerometer and compare its data with the on-board digital accelerometer. This will be done using the TI MSP430 Launchpad board.

Pre-lab Activity

1. What ports will you need on the TI MSP430?

Laboratory Assignments

You may use the PCs in EPIC 2148 or your own PC to do this lab experiment. The machines in EPIC 2148 should already have the software tools loaded. In this lab you will be reading one analog port pin of the TI MSP430 board to read the accelerometer. and write to three port pins to light LEDs. Follow the guidelines for using the device found on the sparkfun.com website (SEN-09652). Also, visit the TI website for more information about the TI MSP430.

Steps

1. Build your hardware system. DO NOT SOLDER components to the TI Launchpad board (only headers). Consider making your own board to hold the SOCKETED TI MSP430 chip.
2. Write the program as one .c and one .h file.
3. Repeat software development until done!
4. Finish lab write-up and demonstrate for the TA.
5. Submit your report and C code (*.c) on Moodle.

Requirements

- Req. 1 - The code generated is written in C for the TI MSP430 Launchpad Board.
- Req. 2 - The code is well commented and easy to follow.
- Req. 3 - The main objective is to use the accelerometer (analog-based) to make a carpenter's level. The long part of the level can be a ruler or any piece of wood/metal that weighs 0.5kg or less and is at least 30cm long.
- Req. 4 - The level electronics part can be any size, but must have at least the socketed MSP430 processor, a power source, an accelerometer, three LEDs, and one button.
- Req. 5 - The level shall work on its own power (i.e. battery), and shall not be tethered during operation.
- Req. 6 - The level need work only in the horizontal plane.
- Req. 6 - The button shall serve as a "calibration" function. When it is pressed, the level (whatever position it is in) shall be declared "level" to earth's gravity and every measurement after that is determined based on the calibration.
- Req. 7 - The level shall operate such that the LEDs of two different colors in a row, center of a different color (i.e. yellow-red-yellow) indicate if the device is level or at an angle. If the device is level, the center light will light up. If the left side is higher, the left LED will light up. If the right side is higher, the right LED will light up. Only one LED should light up at a time.

Req. 8 - The device shall report an angle of 3% or less as level; otherwise, it should light one of the end LEDs.

Lab Report

Include in your lab report observations and procedure like the following:

The general learning objectives of this lab were . . .

Pre-lab question answers

The general steps needed to complete this lab were . . .

Some detailed steps to complete this lab were

1. *Step one*

2. *Step two*

3. *. . . .*

Code generated for this lab...

Some important observations while completing/testing this lab were . . .

In this lab we learned